

FP-PRO-IOB – Input Extension Board IOB

With the input extension board IOB it is possible to equip the 3 already existing inputs (6 inputs featuring diode matrix) that come along with the Video Flashplayer FP-PRO-HD+ with further extensions. Accordingly, it is possible to add the following control commands: SILENT, VOL-, VOL+, PAUSE, STOP, RWD, and FWD. Alternatively, you may also directly hook up 6 pushbuttons (make contacts). Another method to further extend the amount of connectible pushbuttons (make contacts) to a maximum of 12 is to simply add a standard extension that features diodes (e.g. 1N4148). You can cascade up to 4 input extension boards IOB. This way, the Video-Flashplayer FP-PRO-HD+ features a total amount of 48 switch inputs.



Technical Specifications

- Supported remote commands MUTE, VOL-, VOL+, PAUSE, STOP, RWD and FWD
- Alternative connection of up to 6 push buttons (NO contact) or 12 bush buttons (NO contact) with diode matrix
- External connectors RS485-IN and RS485-OUT
- Compact metal case, 90 x 65 x 24 (W x D x H in mm), without connectors
- Working temperature 5 - 40° C, no condensing humidity
- Weight without accessories 120 gram
- Operating voltage will be supplied by Flashplayer FP-PRP-HD+

Areas of Application and Operation

- Support of interactive HD player for museums, exhibitions and science centers
- Support of interactive HD player for kiosk systems and video presenters

Further Information

Content of Delivery:	Input Extension Board IOB WD connecting cable for Flashplayer FP-PRO-HD+
Packaging:	Paperboard container

Technical modifications and errors reserved.